

# PTi845G WEP set up

The screenshot shows the 'Wireless Security' configuration page. At the top, there is a navigation bar with tabs: HOME, EZ SETUP, CONFIG, ADVANCED, WIRELESS (selected), TOOLS, STATUS, and HELP. A left sidebar contains a tree view with 'Security' selected. The main content area is titled 'Wireless Security' and contains the following elements:

- Callout 1: '1. Click on 'Wireless'.' points to the 'WIRELESS' tab in the navigation bar.
- Callout 2: '2. Click on 'Security'.' points to the 'Security' item in the left sidebar.
- Callout 3: '3. Click on the radio button 'WEP'.' points to the 'WEP' radio button under 'Select a Wireless Security level:'.
- Callout 4: '4. Click the tick box (not ticked by default).' points to the 'Enable WEP Wireless Security' checkbox, which is checked.
- Callout 5: '5. Enter the WEP key. i.e 00 00 00 00 00. You must leave a space in between every two characters. This must be hexadecimal: 0-9 & A-F.' points to the first 'Encryption Key' input field, which contains '00 00 00 00 00'.
- Callout 6: '6. Click on 'Apply'.' points to the 'Apply' button at the bottom right.

Additional text on the page includes: 'Authentication Type: Open', 'Cipher' dropdowns set to '64 bits', and a note at the bottom: 'Note: you must [Restart Access Point](#) for Wireless changes to take effect.' 'Apply' and 'Cancel' buttons are visible at the bottom right.

5. Enter the WEP key. i.e 00 00 00 00 00  
You must leave a space in between every two characters. This must be hexadecimal: 0-9 & A-F.

4. Click the tick box (not ticked by default).

8. Click on 'Restart Access Point'.

The screenshot shows a 'Microsoft Internet Explorer' dialog box with a yellow warning icon. The text inside reads: 'Privacy type is set to WEP. Multiple SSID support will be disabled'. An 'OK' button is visible at the bottom, with a mouse cursor hovering over it.

7. Click on the 'OK' button.

HOME EZ SETUP CONFIG ADVANCED WIRELESS **TOOLS** STATUS HELP

**System Commands**

System Commands allow you to carry out basic system actions. Press the button to execute a command.

**Restart**  
Use this button to restart the system. If you have not saved your configurations, the Gateway will revert back to the previously saved configuration upon restarting. NOTE: Connectivity to the unit will be lost. You can reconnect after the unit reboots.

**Restart Access Point**  
Use this button to restart the Wireless Access Point. It is important to Restart Access Point any time you change your Wireless settings.

**Restore Defaults**  
Use this button to restore factory default configuration. NOTE: Connectivity to the unit will be lost. You can reconnect after the unit reboots.

9. Click on the 'Restart Access Point' button.

10. Click on the 'Save All'.

Apply Cancel

11. Click on the 'Apply' button to complete the process.